

# JNP-QSFP-4X10GE-LR

Part number: 740-057315

## Optics Overview

Juniper Networks offers a complete portfolio of modular and fixed-chassis routers and switches for both WAN and data center networks. These solutions span Juniper’s MX-Series Universal Routing Platform and PTX-Series Packet Transport Routers to EX-Series Ethernet Switches and QFX-Series Data Center Switches among others. Depending on deployment scenarios, Juniper’s platforms support different pluggable optic modules that can be selected based on speed, distance, form-factor, and wavelength among other relevant attributes.

## Additional Resources

### Hardware Compatibility Tool

HCT contains a regularly updated database of Juniper’s transceivers, DACs, and AOCs along with information regarding compatibility with Juniper’s platforms and interface modules.

<https://apps.juniper.net/hct/home/>

## Product Description

QSFP+ 40G breakout into 4x10GBASE LR up to 10km SMF, MPO-12 APC Receptacle

## Overview

Part Number	740-057315
Speed	4 x 10 Gigabit Ethernet
Breakout Capable	Yes
Transceiver Type	QSFP+
Product Type	Optical Transceiver
Connector	MPO-12 APC
Monitoring Available	Yes
Digital Optical Monitoring	Yes

Note:

- Monitoring Available - Can measure received optical power and display in CLI.
- Digital Optical Monitoring - Full support for SFF-8636.
- Common Optic - The common optics product line provides competitively priced single-SKU optics offerings for use across Juniper routing, switching, and security platforms.

## Specifications

Standard: 10GBASE-LR, 10GBASE-LW

Standards compliance (Ethernet/OTN Standard, for e.g. 100GBASE-LR4)	IEEE 802.3 Clause 52
Digital Diagnostic Monitoring	Transceiver Temperature Transceiver Supply Voltage Tx Bias Current Tx output power Rx received optical power
Signaling rate, each lane	10GBASE-LR: 10.3125 Gbps 10GBASE-LW: 9.95428 Gbps
Transmitter wavelengths (range)	1260 nm through 1355 nm
Transmitter output power, each lane (minimum)	-6.5 dBm
Transmitter output power, each lane (maximum)	0.5 dBm
Receiver input power, each lane (minimum)	-14.4 dBm
Receiver input power, each lane (maximum)	1.5 dBm
Cable type	SMF
Core size/cladding	9/125 $\mu\text{m}$
Distance	10 km
Maximum Power consumption (W)	3.5 W
Operating Temperature (range)	0° C to 70° C
Storage temperature	-40° C to 85° C

## Supported Platforms

Platform	Introduced Release	Additional Information
Routing		
ACX5000 Breakout Supported		
ACX5448-D Breakout Supported	Junos OS 19.3R1	
ACX5448-M Breakout Supported	Junos OS 19.3R1	
ACX5448 Breakout Supported	Junos OS 18.2R1	
ACX7024 Breakout Supported	Junos OS Evolved 23.1R1	
ACX7100-32C Breakout Supported	Junos OS Evolved 21.3R1	
ACX7100-48L Breakout Supported	Junos OS Evolved 21.3R1	
ACX7509 Breakout Supported	Junos OS Evolved 21.4R1	
PTX10001-36MR Breakout Supported	Junos OS Evolved 20.2R1	
PTX1000 Breakout Supported	Junos OS 16.1X65-D30	
PTX10004 Breakout Supported	Junos OS Evolved 20.3R1	
PTX10008 Breakout Supported	Junos OS Evolved 20.1R1 Junos OS 18.2R1	
PTX10016 Breakout Supported	Junos OS Evolved 21.2R2 Junos OS 18.2R1	
Security		
SRX4600 Breakout Supported	Junos OS 18.1R1	
SRX5400 Breakout Supported	Junos OS 19.3R1	

Platform	Introduced Release	Additional Information
SRX5600 Breakout Supported	Junos OS 19.3R1	
SRX5800 Breakout Supported	Junos OS 19.3R1	
Switching		
EX4300 Multigigabit Breakout Supported	Junos OS 22.1R1	
EX4400 Breakout Supported	Junos OS 23.2R1	
EX4400-48T Breakout Supported	Junos OS 23.2R1	
EX4400-24T Breakout Supported	Junos OS 23.2R1	
EX4400 Multigigabit Breakout Supported	Junos OS 23.2R1	
EX4400-24X Breakout Supported	Junos OS 23.2R1	
EX4400-48F Breakout Supported	Junos OS 23.2R1	
EX4600 Breakout Supported		
EX4650-48Y	Junos OS 23.4R1 Junos OS 20.3R1	
EX9251 Breakout Supported	Junos OS 18.1R1	
EX9253 Breakout Supported	Junos OS 18.2R1	
QFX5100 Breakout Supported		
QFX5110 Breakout Supported	Junos OS 15.1X53-D210	
QFX5120-32C Breakout Supported	Junos OS 20.3R1	

Platform	Introduced Release	Additional Information
QFX5130-32CD Breakout Supported	Junos OS Evolved 22.2R1	
QFX5120-48T Breakout Supported	Junos OS 22.4R1	
QFX5120-48Y	Junos OS 23.4R1 Junos OS 20.3R1	
QFX5120-48YM Breakout Supported	Junos OS 22.2R1	
QFX5200-32C Breakout Supported		
QFX5210-64C Breakout Supported	Junos OS 18.1R1	
QFX5220-32CD Breakout Supported	Junos OS Evolved 22.2R1	
QFX5220-128C Breakout Supported	Junos OS Evolved 22.2R1	
QFX5230-64CD Breakout Supported		
QFX5700 Breakout Supported	Junos OS Evolved 22.2R1	
QFX10002 Breakout Supported	Junos OS 15.1X53-D10	
QFX10008 Breakout Supported	Junos OS 15.1X53-D30	
QFX10016 Breakout Supported	Junos OS 15.1X53-D61	
QFX10002-60C Breakout Supported		

## Supported Interface Modules

### Flexible PIC Concentrators (FPCs)

Name	Description	Platforms and Introduced Releases
40 Gigabit Ethernet		
QFX5K-FPC-16C	16X100G linecard for QFX5700 chassis	QFX5700 Junos OS Evolved 22.2R1 <a href="#">Breakout Supported</a>
QFX5K-FPC-4CD	4X400G linecard for QFX700 chassis	QFX5700 Junos OS Evolved 22.2R1 <a href="#">Breakout Supported</a>
4 x 10 Gigabit Ethernet		
QFX5K-FPC-16C	16X100G linecard for QFX5700 chassis	QFX5700 Junos OS Evolved 22.2R1 <a href="#">Breakout Supported</a>
QFX5K-FPC-4CD	4X400G linecard for QFX700 chassis	QFX5700 Junos OS Evolved 22.2R1 <a href="#">Breakout Supported</a>

### Line Cards

Name	Description	Platforms and Introduced Releases
40 Gigabit Ethernet		
ACX7509-FPC-16C	ACX7509 16X40GE/16X100GE LINE CARD	ACX7509 Junos OS Evolved 21.4R1 <a href="#">Breakout Supported</a>

Name	Description	Platforms and Introduced Releases	
4 x 10 Gigabit Ethernet			
ACX7509-FPC-16C	ACX7509 16X40GE/16X100GE LINE CARD	ACX7509 Junos OS Evolved 21.4R1 <a href="#">Breakout Supported</a>	
EX9253-6Q12C <sup>(EOL)</sup>	A line card with six built-in QSFP+ ports, each of which can house QSFP+ pluggable transceivers and 12 built-in QSFP28 ports, each of which can house QSFP28 pluggable transceivers.	EX9253 Junos OS 18.2R1 <a href="#">Breakout Supported</a>	
EX9253-6Q12C-M <sup>(EOL)</sup>	A line card with six built-in QSFP+ ports, each of which can house QSFP+ pluggable transceivers and 12 built-in QSFP28 ports with Media Access Control Security (MACsec) capability, each of which can house QSFP28 pluggable transceivers.	EX9253 Junos OS 18.2R1 <a href="#">Breakout Supported</a>	
PTX10K-LC1105	PTX10K 3Tbps MACse Line Card - 30x100G/30x40G	PTX10008 Junos OS 18.2R1 <a href="#">Breakout Supported</a>	PTX10016 Junos OS 18.3R1 <a href="#">Breakout Supported</a>
PTX10K-LC1201-36CD	PTX10K 36 ports of 400 Gigabit Ethernet that provide 14.4-Tbps line rate processing speeds	PTX10004 Junos OS Evolved 20.3R1 <a href="#">Breakout Supported</a>	PTX10008 Junos OS Evolved 20.1R1 <a href="#">Breakout Supported</a>
		PTX10016 Junos OS Evolved 21.2R2 <a href="#">Breakout Supported</a>	
PTX10K-LC1202-36MR	36-port line card that has thirty-two QSFP28 ports capable of supporting 100-Gbps speed, and four QSFP56-DD ports capable of supporting 400-Gbps speed	PTX10004 Junos OS Evolved 20.4R1 <a href="#">Breakout Supported</a>	PTX10008 Junos OS Evolved 20.3R1 <a href="#">Breakout Supported</a>
		PTX10016 Junos OS Evolved 21.2R2 <a href="#">Breakout Supported</a>	

Name	Description	Platforms and Introduced Releases	
QFX10000-36Q	A 36-port 40-Gigabit Ethernet quad small form-factor pluggable plus transceiver (QSFP+) or 12-port 100GbE QSFP28 line card	QFX10008 Junos OS 15.1X53-D30 Breakout Supported	QFX10016 Junos OS 15.1X53-D61 Breakout Supported

## Uplink Modules

Name	Description	Platforms and Introduced Releases	
4 x 10 Gigabit Ethernet			
EX-UM-2QSFP-MR	EX4300MP 2-port 40GbE QSFP+/1-port 100GbE QSPF28 Uplink Module for EX4300-48MP	EX4300 Multigigabit Junos OS 22.1R1 Breakout Supported	
EX4400-EM-1C	1x100GbE QSFP28 extension module for EX4400 series of switches	EX4400-24X Junos OS 23.4R1 Breakout Supported	



## Why buy optics from Juniper?

There is value in choosing Juniper over 3<sup>rd</sup> party optics

### ✓ Full testing, validation, and JTAC support for Juniper optics

- Power, Electrical, and Management interfaces tested at the system level.
- Extended temperature and functional testing in DVT chamber using fully loaded systems.
- Full software integration into JUNOS/EVO for seamless part recognition, functionality, and telemetry.
- Latest qualification status and optics specifications published on [Hardware Compatibility Tool](#).

### ✓ Single-source provider for 1G to 400G on a variety of optical technologies

- Juniper's optics portfolio is maintained and constantly refreshed based on vendor availability.
- Automatic supply chain diversity and supply continuity - multiple optics suppliers fulfilled through Juniper.

### ✓ Rigorous evaluation of optical vendors

- Juniper ensures uniformity across all vendors by standardizing P-Specs for management, specs, and logs.
- Vendors are scored based on engineering and supply-chain analysis.
- Factory audits and critical component evaluation (Ex. Who is supplying the laser?).

## Aren't 3<sup>rd</sup> party optics the same?

Optics may be a commodity, but some things are too good to be true

### × Juniper does not Provide JTAC support for 3<sup>rd</sup> party optics

- JTAC will only assist with host-related issues unrelated to the use of 3<sup>rd</sup> party optics.

### × Not all optics are the same - standards compliance does not guarantee quality or performance

- Third-party providers lack system-level knowledge and testing.
- No guarantee of vendor reliability or accountability.

### × Newer technologies (ex. Coherent 400G ZR/ZR+) are complex and not simply plug-and-play

- Significant software integration necessary to enable full functionality, management, and telemetry.
- Use of unqualified 3<sup>rd</sup> party high-power optics can damage the host equipment.

### × Third-party providers simply can't scale

- Incomplete solution offerings and fast turnaround times only for limited quantities.

---

Copyright © 2024, Juniper Networks, Inc. All rights reserved.

By accessing information contained in this document, you agree that:

- the information you are accessing is confidential to Juniper Networks
- you will not disclose this information to any party outside Juniper Networks
- you are authorized by Juniper Networks to access the information

The information in this document is provided "AS IS", with no warranties of any kind attached to the information. Any reliance upon the information shall be at the user's own risk. Juniper assumes no liability for the information contained in this document.